

**16-Zone speaker selector AL-16S4**

**Features:**

- ▶ This speaker selector controls up to 16 speaker outputs and 4 audio inputs.
- ▶ Flexible multi-input speaker selector arranged in a 4 x 4 matrix with priority override. 16 speaker zones are divided into 4 groups, each group can have a separate audio source.
- ▶ A priority bus is provided to mute background music for zone paging and emergency alarms.



**SPECIFICATIONS AL-16S4**

Input	4 program and 1 priority channels, 70/100V audio signal
Speaker Output	4 groups of 4 zones, 70/100V audio signal
Priority Bus	16 channels, activated by 0V signal
Power Handling	1.5kW total capacity, 375W per channel
Alarm Output	0V signal
Controls	16 pushbutton zone selectors, 1 power switch
Power Requirements	110-120V or 220-240V AC, 50/60 Hz; 24VDC
Dimensions	89(H) x 483(W) x 366(D) mm

**2\*5 10 Zone speaker selector AL-10S2**

**Features:**

- ▶ High power handling and flexible model with 2 amplifier inputs and 2 groups of speaker outputs the AL-10S2
- ▶ Two 5-zone speaker selectors with separate audio sources or as a 10-zone selector with a single audio source.



**SPECIFICATIONS AL-10S2**

Input	2 program channels, 70/100V audio signal
Speaker Output	2 groups of 5 zones, 70/100V audio signal
Priority Bus	N/A
Power Handling	1.5kW total capacity, 150W per zone
Alarm Output	N/A
Controls	10 pushbutton zone selectors, 1 power switch
Power Requirements	110-120V or 220-240V AC, 50/60 Hz; 24VDC
Dimensions	89(H) x 483(W) x 366(D) mm