



### Dante Bluetooth Wall panel

#### Description:

Dante BW 0202 is a wall panel for converting between Bluetooth and Dante signal, achieving two-way stereo transmission. It is widely used for teleconference, audio media transmission, etc.

#### Features:

- ▶ CAT5/6 connector to link with Dante network and controlled by Audinate;
- ▶ Small size integrated mounting bracket which can be installed in very limited space;
- ▶ Adopt advanced V5.0 Bluetooth technology;
- ▶ Simple to pair bluetooth by pressing a button;
- ▶ Compatible with a variety of mobile phones, tablets, computers and other devices;
- ▶ Support PoE power supply;
- ▶ Integrated power supply and audio transmission in one body
- ▶ Convert 1 Bluetooth Audio signal to 2 Dante Network Audio channels



Model	Dante BW 0202
Dante Audio Channel	2
Bluetooth Interface	Bluetooth 5.0, stereo input and output
Dante Interface	RJ45 interface, stereo input and output
Sampling Rate	48KHz, 24bit
Noise floor	-90dB
Power consumption	2W
THD	Less than 0.005%
Freq. Response	20~20KHz
Power Requirements	POE
Operating temperature	-10°C- 40°C
Working humidity	5-95%
Dimensions	123.5 × 79 × 35mm
Net weight	156g

### Dante Bluetooth Wall panel



#### Description:

Dante BW 0404 is a wall panel for converting among analog, Bluetooth and Dante signal. It is widely used for teleconference, audio long-distance transmission and other applications.

#### Features:

- ▶ CAT5/6 connector to link with Dante network and controlled by Audinate;
- ▶ Small size integrated mounting bracket which can be installed in very limited space;
- ▶ Adopt advanced V5.0 Bluetooth technology;
- ▶ Simple to pair Bluetooth by pressing a button;
- ▶ Compatible with a variety of mobile phones, tablets, computers and other devices;
- ▶ With RCA and 3.5mm TRS stereo input, TRS priority;
- ▶ With one 3.5mm TRS stereo output;
- ▶ Support PoE power supply;
- ▶ Integrated power supply and audio transmission in one body;
- ▶ With Bluetooth call bridge function for conference purposes
- ▶ Convert 1 Bluetooth Audio signal to 2 Dante network audio channel;
- ▶ Convert 1 aux or 3.5 jack stereo to 2 Dante network audio channel.
- ▶ Receiving Dante network audio signal via local 3.5 jack

Model	Dante BW 0404
Dante Audio Channel	4
Input Interface	Bluetooth 5.0, stereo, RCA*2, 3.5mm TRS*1
Output Interface	Bluetooth 5.0, stereo, 3.5mm TRS*1
SNR	>100dB
Noise floor	-90dB
Power consumption	2W
THD	Less than 0.005%
Freq. Response	20~20KHz
Power Requirements	POE
Operating temperature	-10°C - 40°C
Working humidity	5-95%
Dimensions	123.5 × 109.1 × 30mm

