



SIP-TL2, Indoor 2 button Terminal
With built-in 2*15W 8 ohm amplifier



SIP-TL1, Indoor 1 button Terminal

- ▶ Professional SIP terminals working with Lucky Tone SIP microphone, other SIP telephones and devices.
- ▶ Adopt high-speed industrial grade chip
- ▶ Support quiet and noisy environment mode, press to answer or auto answer, hangup on site or remote

- ▶ Built-in speaker for intercom
- ▶ With audio output for external active speaker
- ▶ Can work stand alone without any main control unit

outdoor Terminals



SIP-TLO2, Outdoor 2 button Terminal
With built-in 2*15W 8 ohm amplifier



SIP-TLO1, Outdoor 1 button Terminal

Model	SIP-TL indoor	SIP-TLO Outdoor
Network Communication Protocol	TCP, ARP, ICMP, DHCP, UDP, DNS, IGMP	TCP, ARP, ICMP, DHCP, UDP, DNS, IGMP
Network Interface	10/100Base-TX, RJ45	10/100Base-TX, RJ45
Frequency and Sampling Rate	8kHz~32 kHz, 16 bit	8kHz~32 kHz, 16 bit
Power consumption	Less than 300mV	Less than 300mV
Microphone Frequency Range	70Hz~12.5KHz	70Hz~12.5KHz
Operating Temp.	0~65°C	-40~80°C
Weight	0.5kg	0.7kg
Power Supply	DC 12V	DC 12V
Dimension	100 x 160 x 30 mm	150 x 190 x 36 mm