



6 Zone Mixer Amplifier with Zone volume control



Mplayer A



Mplayer B



Mplayer C

3 types of Media Player for you to choose to add to the Amplifier



Optional Mounts for assembly in 19 rack, Ordering code: RKM-01

Features:

- ▶ Controls
  - Front : 4 Input Channel Volume Control and 1 selectable source input Volume control, Master Volume Control, 6 Zone Speaker Selector with 6 step attenuator.
  - Rear : Talkover Switch ( VOX ) & Phantom Power Switch for Channel 1-4. Chime enable with volume control.
  - Bypass contact input & system mute.
- ▶ Connectors
  - Input : Channel 1 - 4 : Electronically Balanced with chime switch.
  - Aux : Dual RCA.
  - Remote Mic : Rj45.
  - Emergency Alarm input : Euro block.
  - Output : Speaker Output : Euro Block . Attenuated and Switched 6 CH, Direct Output 4Ω, 70V, 100V.
  - REC Out & Link out : RCA.
  - Contact : Ext. Chime : Euro block.
  - MUTE : Euro block.
- ▶ Media player module : MPlayer A / MPlayer B / MPlayer C.
- ▶ Indicators : SIG, -10dB, CLIP & Protect. Zone selector.
- ▶ Protection : Output Current Limiting, Thermal Protection & DC Offset Protection.
- ▶ Cooling : Convection Cooling.
- ▶ Option : Rack Mount Kit.



MODEL	Mpro 130	Mpro 240	Mpro 360	Mpro 480
Rated Power (RMS)	130W	240W	360W	480W
Input sensitivity/Impedance	Channel 1-4 -36dB / -10dB Selectable / 20 kΩ Balanced			
	Aux 0dB / 20 kΩ Balanced			
	Remote Mic 0dB / 20 kΩ Balanced			
Output level/Impedance	Speaker Hi-z 100V(83 Ω), 70V(42 Ω)	100V(42 Ω), 70V(21 Ω)	100V(28 Ω), 70V(14 Ω)	100V(21 Ω), 70V(10 Ω)
	Output Low-z 22V (4 Ω)	31V (4 Ω)	38V (4 Ω)	43V (4 Ω)
	Rec Out 0dB / 600 Ω Unbalanced			
	Link Out 0dB / 600 Ω Unbalanced			
Frequency Respose (-3dB)	65Hz - 18kHz			
T.H.D (1kHz, Rated Power)	<1%			
Signal to Noise Ratio	>80dB			
Tone Control	± 10dB			
	100Hz , 10KHz			
Power Source	AC 115 / 230 V, 50/60Hz			
Weight (Net)	9 kg	10kg	11kg	12kg
Dimensions (W x H x D)	420 x88 x 320mm			