

## DAB Amplifier

### Description:

Lucky Tone DAB amplifier series is a compact digital mixer amplifier with a 30W/60W (rms) output ideal for comfortable background music in both commercial and domestic environments. The DAB-30 and 60 weighs just 2.16kg so it can sit on or below a desk, in a drawer or a cabinet.

This versatile mixer amp features Bluetooth connectivity, an DAB (Digital Audio Broadcasting) tuner, and USB input perfect for connecting almost any device. It also has a 6.35mm and XLR microphone input great for making announcements, last calls, or even pub quizzes.

Mono output to either 100V line, 70V line or 4–16 ohms speaker load is connected via phoenix terminals on the rear panel.

Boasts a simple-to-use digital interface with onboard controls such as mode, play/pause, next/previous, and repeat.

Software adjustment: digital Effect, EQ, Priority and super bass

### Suggested areas of use:

Domestic Environments | Lounges | Dining Areas | School Classrooms  
Commercial Environments | Retail stores | Cafes | Coffee Shops | Offices



### SPECIFICATIONS

### DAB-30/DAB-60

Power supply	220–240Vac, 50Hz/60Hz (IEC) or 12VDC back up power
Audio source	USB player, DAB tuner and Bluetooth receiver
Bluetooth version	5.0; compatible 4.2 and V2.1EDR
Controls	Treble, Master, MP3, Aux, Mic
Microphone inputs	6.3mm jack (unbalanced) and XLR (balanced)
Line input	2 x RCA (summed to mono)
Line output	1 x RCA
Speaker outputs	COM, 100V/70V and 4–16 Ohms (Phoenix terminals)
Antenna connection	screw terminal
Dimensions	280 x 205 x 67mm
Power output	30W / 60W RMS
Weight	2.16/ 2.36kg