

DAB Amplifier

Description:

Lucky Tone DAB amplifier series is a compact digital mixer amplifier with a 30W/60W (rms) output ideal for comfortable background music in both commercial and domestic environments. The DAB-30 and 60 weighs just 2.16kg so it can sit on or below a desk, in a drawer or a cabinet.

This versatile mixer amp features Bluetooth connectivity, an DAB (Digital Audio Broadcasting) tuner, and USB input perfect for connecting almost any device. It also has a 6.35mm and XLR microphone input great for making announcements, last calls, or even pub quizzes.

Mono output to either 100V line, 70V line or 4-16 ohms speaker load is connected via phoenix terminals on the rear panel.

Boasts a simple-to-use digital interface with onboard controls such as mode, play/pause, next/previous, and repeat.

Software adjustment: digital Effect, EQ, Priority and super bass

Suggested areas of use:

Domestic Environments | Lounges | Dining Areas | School Classrooms

Commercial Environments | Retail stores | Cafes | Coffee Shops | Offices



SPECIFICATIONS

DAB-30/DAB-60

Power supply	220-240Vac, 50Hz/60Hz (IEC) or 12VDC back up power
Audio source	USB player, DAB tuner and Bluetooth receiver
Bluetooth version	5.0; compatible 4.2 and V2.1EDR
Controls	Treble, Master, MP3, Aux, Mic
Microphone inputs	6.3mm jack (unbalanced) and XLR (balanced)
Line input	2 x RCA (summed to mono)
Line output	1 x RCA
Speaker outputs	COM, 100V/70V and 4-16 Ohms (Phoenix terminals)
Antenna connection	screw terminal
Dimensions	280 x 205 x 67mm
Power output	30W / 60W RMS
Weight	2.16/ 2.36kg