

10 Zone speaker selector AL-10S
Features:

- ▶ With flexible A/B amplifier inputs for auto switch from BGM and Emergency amplifier
- ▶ Control up to 10 speaker zone outputs
- ▶ Essential for analog medium PA system
- ▶ LED status indicators
- ▶ 10-channel priority bus
- ▶ 2 alarm activation outputs


SPECIFICATIONS
AL-10S

Input	1 program and 1 priority channels, 70/100V audio signal
Speaker Output	1 group of 10 zones, 70/100V audio signal
Priority Bus	10 channels, activated by 0V signal
Power Handling	1.5kW total capacity, 150W per zone
Alarm Output	0V signal
Controls	10 pushbutton zone selectors, 1 power switch
Power Requirements	110-120V or 220-240V AC, 50/60 Hz; 24VDC
Dimensions	89(H) x 483(W) x 366(D) mm