

Pre- Amplifier AL-11P

With multi versatile inputs

Features:

- ▶ The AL-11P is a versatile mixer pre-amplifier with 4 microphone inputs, 3 auxiliary inputs, 2 emergency inputs (high priority) and mute function.
- ▶ MIC1, EMC1, EMC2 are priority inputs, automatically muting all other signal inputs. MIC1 has the highest priority, able to suppress all other inputs.
- ▶ With bass and treble control, automatic mute function for paging and individual gain control for all the inputs.



SPECIFICATIONS AL-11P

| | |
|--------------------|--|
| Input | MIC 1, 2, 3, 4: 600 ohms, 5mV, unbalanced, phone jack AUX 1, 2, 3: 10k ohms, 200mV, unbalanced, RCA jack EMC 1, 2: 10k ohms, 200mV, unbalanced, phone jack |
| Output | 600 ohms, 775mV, 0 dB, RCA jack |
| Frequency Response | 60Hz – 15kHz (+/- 3dB) |
| S/N Ratio | Better than 70dB |
| THD | Less than 0.1% at 1kHz |
| Tone Controls | BASS: 100 Hz (+/- 10dB), TREBLE: 12k Hz (+/- 10dB) |
| Muting Function | MIC1 overrides other input signals with 0 30 dB attenuation EMC1 overrides other input signals except MIC 1 |
| Power Requirements | 220–240V AC, 50/60 Hz |
| Dimensions | 89(H) x 483(W) x 366(D) mm |

10-CHANNEL MONITOR PANEL AL-10M

Features:

- ▶ With built-in high fidelity loudspeaker monitoring up to 10 zones. 6 LED dB level meter clearly indicate the channel level status.
- ▶ The monitoring volume is adjustable as well as the 10 channel position selection.



SPECIFICATIONS AL-10M

| | |
|---------------------|---|
| Input | 70/100V audio signal |
| Monitored Channels | 10 |
| Audible Monitor | Full-range loudspeaker, 500mW |
| Visual Monitor | 6-element LED display, infinite, 0, 2, 4, 6, 8, 10 dB |
| Controls | Monitor volume, channel select and power switch |
| Indicators | Power LED |
| Protection | AC Fuse: 0.5A |
| Power Consumption | 10–15 watts |
| Power Requirements | 110–120V or 220–240V AC, 50/60 Hz; 24VDC |
| Dimensions | 89(H) x 483(W) x 366(D) mm |
| Built-in Dimensions | 2 U rack 19 inch |
| Net Weight | 6.1kg |