

**4 Channel Output module for Open architecture  
DSP-6464LD+ or DSP-3232LD+**
**Description:**

The analog output card provides 4-channel line output. DSP-AO4 LD+ employs electronically balanced outputs and plug-in connectors. Control functions for each output include: gain level and mute control.

**Features:**

- ▶ 4 balanced line outputs
- ▶ Easy for installation
- ▶ Control and configure via software


**SPECIFICATIONS**
**DSP-AO4 LD+**

Dynamic range	>118dB
Frequency response ( $\pm 0.2$ dB)	20Hz~20kHz
Output impedance	102 $\Omega$
Channel Crosstalk	<-112dB
THD+N	<0.002%
Maximum output level (@1% distortion)	+22dBu
Interface	four 3-pin Euro breakaway terminals