


8-CH Bluetooth wall amplifier with Android







This 8-channel small bluetooth multi-home audio system equipped with micro USB/TF can power 8 to 16 pieces of speakers in your home or small commercial area. It uses a high-efficiency class-D amplifier for a maximum output of 8*25 watts, low-impedance speakers. The cool display shows relevant track music info. Plus, you can control everything -seek, change tracks, and adjust the volume - using the included wireless infrared remote controller.




Default silver rim with white color inner; gold rim with black color inner optional

The APPs can be installed by user depending on needs.

Features:

- ▶ 2 Zone control of music, 10 inch touch screen for easy access and control of the system
- ▶ Multi-protocol smart home docking including, WIFI, etc.
- ▶ Can install Spotify, Pandora music APPs to play real time music via WiF
- Support for external Bluetooth devices such as mobile phones to achieve audio playback, two-way control of playing external Bluetooth device music.
- ▶ Support audio input and output function; support subwoofer access;
- ▶ Support TF card and USB interface, USB can be connected to the hard
- ▶ disk;

Suitable for homes, commercial areas, kid's room, etc.



SPECIFICATIONS	BA-1025ADX
Output power	8*25W
Max. power	8*50W
Speaker Impedance	4-8ohm
System	Android 5.1
RAM	1GB
ROM	8GB
Network	WIFI
CPU	ARM Quad-Core Cortex-A35 1.5GHz
Display	10inch HD touch screen
Resolution	1024*600 IPS
Bluetooth wireless range	10M
USB	Micro USB port
THD	0.03% (1W.1KHZ)
Frequency response	20 Hz-20 kHz (+/-2dB)
SNR	98db
Music format	Mp3, WMA, WAV, AAC, WAW, APE, OGG, etc.
Video format	MPEG-1/2/3/4, RM/RMVB, WMV, MOV, MK, VOB,
	AVI, 3GP, H, 264, etc.
Power Requirements	110-250VAC
Wiring box size	180*106*69mm
Product size	251*160*50mm
Weight	1 kg